

ReadMe

Upgrade Instructions from 1.13 or 2.6:

- Use Scan Controller Utility to back up all XML files on Controller
- Download and unzip Upgrade-to-3.4.ipg
- Using Scan Controller Utility:
 - Lock Scanner by clicking on lock symbol.
 - Click on "Upgrade Scanner"
 - Change to ".ipg" extension in dialog box.
 - Select Upgrade-to-3.4.ipg"
- Upgrade takes 1/2 Hour. Do not power cycle!!!
 - If Utility does not complete after 1/2 Hour, power cycle **Once** and wait an additional 1/2 Hour.
 - Scan Controller should be visible from Utility.
 - If process Fails, a Re-Image is needed. (see image directory)

Note: Additional status information can be monitored by looking at the Serial Port of The scan controller.

115200 Baud

8 Bit Data

No Parity

No Flow