

Upgrade Instructions from 3.4 or 3.5

Use Scan Controller Utility to back up all XML files on Controller

Download upgrade-to-3.7.4-customer-r16960.ipg

Using Scan Controller Utility:

Lock Scanner by clicking on lock symbol.

Click on "Upgrade Scanner"

Change to ".ipg" extension in dialog box.

Select "upgrade-to-3.7.4-customer-r16960.ipg"

Upgrade takes 15 minutes and the scan controller reboots 3 times. Do not power cycle!!!

When upgrade completes, Scan Controller is visible from Utility.

If process Fails, a Re-Image is needed. (see image directory)

Note: Additional status information can be monitored by looking at the serial port of The scan controller.

115200 Baud

8 Bit Data

No Parity

No Flow